

# CAMERA

## B/W Cameras

# B/W 420TVL

## Standard-Resolution Camera

### ED100

#### 1/3" B/W 420TVL Sony CCD Mini Dome Camera

##### Features

- Low light sensitivity (0.04 lux/F=1.2/AGC ON) is achieved by using the advanced 1/3" Sony CCD image sensor
- The electronic shutter and AGC allow the camera to be used in environments with varying light levels
- Built-in audio function
- Compact size: 103mm O.D. x 30mm H
- Available for CCIR and EIA



##### Specification

Video format	EIA or CCIR
Picture element	EIA:510(±4%)CCIR:500(±0.8%)
Horizontal resolution	420 TV lines
Sensitivity	0.04 lux / F=1.2
S/N ratio	Over 48 dB
Electronic shutter	1/60(1/60) - 1/100,000 Sec.
Back light comp.	Yes
Auto gain control	On
Gamma correction	>0.45
Sync. mode	Internal Sync.
Power source	12VDC ±12%, 150mA
Dimension	103(O.D.)x30(H.) (mm)
Operating temperature	0 °C ~ +50 °C, 20~80%
Weight	330g
Lens	Board lens f=3.6mm, F=2.8 (Optional: 2.5/4.3/6.0/8.0mm, Pinhole 3.7mm)

\* Further details see table page 23

##### Ordering Information

- **ED100E-3B**: Dome camera with standard 3.6mm lens and black base and Sony CCD chip. To order additional lenses, replace the last number with the first digit(s) of the lens desired: 2.5mm(E-2B), 4.3mm(E-4B), 6.0mm(E-6B), 8.0mm(E-8B), 12.0mm(E-12B) and 16.0mm(E-16B)

B/W  
5A,3000

EB  
1/14,300

B.L.C  
ON

AGC  
ON

DC  
-OFF



## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>